

INSTALLATION INSTRUCTIONS

Current Transformer Kits (with Mounting Brackets) Used on Safeguard Circuit Breaker Kits and Controllers without Meters 20-150 kW Standby Generator Sets

Applications for generator set models may vary depending upon voltage/frequency connection. Contact an authorized distributor/dealer for proper selection of kit.

PA-275491	PA-276188	PA-276988
PA-275492	PA-276189	PA-275492-SD
PA-275496	PA-276190	PA-275496-SD
PA-275499	PA-276983	PA-275499-SD
PA-275505	PA-276984	PA-275515-SD
PA-275508	PA-276985	PA-276983-SD
PA-275511	PA-276986	PA-276984-SD
PA-276187	PA-276987	

WARNING



Accidental starting.

Can cause severe injury or death.

Disconnect battery cables before working on generator set (negative lead first and reconnect it last).

Accidental starting can cause severe injury or death. Turn generator master switch to OFF position, disconnect power to battery charger, and remove battery cables (remove negative lead first and reconnect it last) to disable generator set before working on any equipment connected to generator. The generator set can be started by automatic transfer switch or remote start/stop switch unless these precautions are followed.

WARNING



Hazardous voltage.



Moving rotor.

Can cause severe injury or death.

Do not operate generator set without all guards and electrical enclosures in place.

Hazardous voltage can cause severe injury or death. Disconnect set from load by opening line circuit breaker or by disconnecting generator output leads from transfer switch and heavily taping ends of leads. If high voltage is transferred to load during test, personal injury and equipment damage may result. The GENERATOR SAFEGUARD BREAKER MUST NOT BE USED IN PLACE OF LINE CIRCUIT BREAKER!

INSTALLATION

1. Move generator master switch to OFF position.
2. Remove generator set battery cables, negative lead first.

3. Mount current transformers to bracket (273967) using 12, 10-24 x 0.625-in. r.h.m. screws (X-50-8), 0.219 x 0.500 x 0.049-in. plain washers (X-25-36), and 10-24 whiz nuts (X-6210-5). See Figures 1 and 2. Items referred to in Figure 2 apply to Figure 1.

NOTE

Mount current transformer with dot or HI toward generator.

NOTE

Brackets are not required in kits PA-276988 and PA-275515-SD.

NOTE

Generator sets with 120-240 volt connections require one turn of output leads through current transformer. Generator sets with 480-600 volt connections require two turns of output leads through current transformer.

4. Mount bracket assembly to generator junction box using four 10-24 x 0.50-in. Phillips® Crimptite® screw (X-6216-1).
5. Remove 1B from safeguard terminal strip (terminal 70) and connect to safeguard breaker pole 2-load terminal. See Figure 3 for location of safeguard circuit breaker. Make remaining current transformer connections as shown in Figures 4

and 5. Items referred to in Figure 5 apply to Figure 4. See Figure 6 for voltage reconnection.

6. Reconnect generator set battery cables, negative lead last.
7. Move generator set master switch to normal operating position.




Figure 1. Current Transformer Mounting

Kit No.	Item A Current Transformer	Item B Bracket	Item C Bracket Mounting Screw	Item D Current Transformer Mounting Hardware (Screw, Plain Washer, Whiz Nut)
PA-275491	259359 (3)	273967	X-6216-1 (4)	X-50-8 (12), X-25-36 (12), X-6210-5 (12)
PA-275492 PA-275492-SD	259360 (3)	273967	X-6216-1 (4)	X-50-8 (12), X-25-36 (12), X-6210-5 (12)
PA-275496 PA-275496-SD	259414 (3)	273967	X-6216-1 (4)	X-50-8 (12), X-25-36 (12), X-6210-5 (12)
PA-275499 PA-275499-SD	255860 (3)	273967	X-6216-1 (4)	X-50-8 (12), X-25-36 (12), X-6210-5 (12)
PA-275505	253503 (3)	273967	X-6216-1 (4)	X-50-8 (12), X-25-36 (12), X-6210-5 (12)
PA-275508	273257 (3)	273967	X-6216-1 (4)	X-50-8 (12), X-25-36 (12), X-6210-5 (12)
PA-275511	253610 (3)	273967	X-6216-1 (4)	X-50-8 (12), X-25-36 (12), X-6210-5 (12)
PA-276187	255860 (3)	273967	X-6216-1 (4)	X-50-8 (12), X-25-36 (12), X-6210-5 (12)
PA-276188	253503 (3)	273967	X-6216-1 (4)	X-50-8 (12), X-25-36 (12), X-6210-5 (12)
PA-276189	273257 (3)	273967	X-6216-1 (4)	X-50-8 (12), X-25-36 (12), X-6210-5 (12)
PA-276190	253610 (3)	273967	X-6216-1 (4)	X-50-8 (12), X-25-36 (12), X-6210-5 (12)
PA-276983 PA-276983-SD	259793 (3)	273967	X-6216-1 (4)	X-50-8 (12), X-25-36 (12), X-6210-5 (12)
PA-276984 PA-276984-SD	259792 (3)	273967	X-6216-1 (4)	X-50-8 (12), X-25-36 (12), X-6210-5 (12)
PA-276985	259359 (3)	273967	X-6216-1 (4)	X-50-8 (12), X-25-36 (12), X-6210-5 (12)
PA-276986	259360 (3)	273967	X-6216-1 (4)	X-50-8 (12), X-25-36 (12), X-6210-5 (12)
PA-276987	259414 (3)	273967	X-6216-1 (4)	X-50-8 (12), X-25-36 (12), X-6210-5 (12)

**Figure 2. Hardware for Current Transformer Kits
(Items are referenced in Figure 1.)**





Figure 3. Safeguard Breaker Locations


Kit No.	Item E	Item F	Item G	Item H	Item J
PA-275491	SWC0-1830-1414	SWC1-1830-1414	SWC2-1830-1414	SWC3-1830-1414	SWC0-1808-1313 (2)
PA-275492 & PA-275492-SD	SWC0-1830-1414	SWC1-1830-1414	SWC2-1830-1414	SWC3-1830-1414	SWC0-1808-1313 (2)
PA-275496 & PA-275496-SD	SWC0-1830-1414	SWC1-1830-1414	SWC2-1830-1414	SWC3-1830-1414	SWC0-1808-1313 (2)
PA-275499 & PA-275499-SD	SWC0-1830-1414	SWC1-1830-1414	SWC2-1830-1414	SWC3-1830-1414	SWC0-1808-1313 (2)
PA-275505	SWC0-1830-1414	SWC1-1830-1414	SWC2-1830-1414	SWC3-1830-1414	SWC0-1808-1313 (2)
PA-275508	SWC0-1830-1414	SWC1-1830-1414	SWC2-1830-1414	SWC3-1830-1414	SWC0-1808-1313 (2)
PA-275511	SWC0-1830-1414	SWC1-1830-1414	SWC2-1830-1414	SWC3-1830-1414	SWC0-1808-1313 (2)
PA-276187	SWC0-1830-1414	SWC1-1830-1414	SWC2-1830-1414	SWC3-1830-1414	SWC0-1808-1313 (2)
PA-276188	SWC0-1830-1414	SWC1-1830-1414	SWC2-1830-1414	SWC3-1830-1414	SWC0-1808-1313 (2)
PA-276189	SWC0-1830-1414	SWC1-1830-1414	SWC2-1830-1414	SWC3-1830-1414	SWC0-1808-1313 (2)
PA-276190	SWC0-1830-1414	SWC1-1830-1414	SWC2-1830-1414	SWC3-1830-1414	SWC0-1808-1313 (2)
PA-276983 & PA-276983-SD	SWC0-1830-1414	SWC1-1830-1414	SWC2-1830-1414	SWC3-1830-1414	SWC0-1808-1313 (2)
PA-276984 & PA-276984-SD	SWC0-1830-1414	SWC1-1830-1414	SWC2-1830-1414	SWC3-1830-1414	SWC0-1808-1313 (2)
PA-276985	SWC0-1830-1414	SWC1-1830-1414	SWC2-1830-1414	SWC3-1830-1414	SWC0-1808-1313 (2)
PA-276986	SWC0-1830-1414	SWC1-1830-1414	SWC2-1830-1414	SWC3-1830-1414	SWC0-1808-1313 (2)
PA-276987	SWC0-1830-1414	SWC1-1830-1414	SWC2-1830-1414	SWC3-1830-1414	SWC0-1808-1313 (2)
PA-276988	SWC0-1830-1414	SWC1-1830-1414	SWC2-1830-1414	SWC3-1830-1414	SWC0-1808-1313 (2)
PA-275515-SD	SWC0-1630-1423	SWC1-1635-1414	SWC2-1635-1414	SWC3-1635-1414	LW-1608-1414 (2)

**Figure 4. Current Transformer Leads
(Items are referenced in Figure 5.)**

Figure 5. Current Transformer Circuit Connections




60 Hz—120/240 V—1 PHASE 3 WIRE
 50 Hz—110/220 V—1 PHASE 3 WIRE
 USED ON GENERATORS 20 kW–100 kW ONLY.




TB2 METER SCALE
LAMP JUMPER

60 Hz—120/240 V—3 PHASE 4 WIRE DELTA
 50 Hz—110/220 V—3 PHASE 4 WIRE DELTA




TB2 METER SCALE
LAMP JUMPER

60 Hz—120/208 V OR 139/240 V
 3 PHASE 4 WIRE LOW WYE
 50 Hz—120/208 V OR 110/190 V
 3 PHASE 4 WIRE LOW WYE




TB2 METER SCALE
LAMP JUMPER

60 Hz—277/480 V—3 PHASE 4 WIRE HIGH WYE
 50 Hz—220/380 V—3 PHASE 4 WIRE HIGH WYE



TB2 METER SCALE
LAMP JUMPER

6 LEAD STATOR
 600 VOLT



NOTE: TWO TURNS THROUGH CURRENT
TRANSFORMER.

TB2 METER SCALE
LAMP JUMPER

GENERATOR CONNECTIONS

DE-273000-D P1

Figure 6. Generator Connections

Parts List		
Kits: PA-275491, PA-275505, PA-275508, PA-275511, PA-276985, PA-275492, PA-275492-SD, PA-275496, PA-275496-SD, PA-275499, PA-275499-SD, PA-276983, PA-276983-SD, PA-276984, and PA-276984-SD		
Description	Qty.	Part No.
Lead	2	SWC0-1808-1313
Lead	1	SWC0-1830-1414
Lead	1	SWC1-1830-1414
Lead	1	SWC2-1830-1414
Lead	1	SWC3-1830-1414
Washer, 0.219 x 0.500 x 0.049 in. plain	12	X-25-36
Tie, cable	2	X-468-2
Screw, 10-24 x 0.625 in. r.h.m.	12	X-50-8
Jumper	1	X-6076-2
Nut, 10-24 whiz	12	X-6210-5
Screw, 10-24 x 0.50 in. Phillips® Crimptite®	4	X-6216-1
Bracket	1	273967
Transformer, current (Kit PA-275491)	3	295359
Transformer, current (Kit PA-275505)	3	253503
Transformer, current (Kit PA-275508)	3	273257
Transformer, current (Kit PA-275511)	3	253610
Transformer, current (Kit PA-276985)	3	259359
Transformer, current (Kits PA-275492 and PA-275492-SD)	3	259360
Transformer, current (Kits PA-275496 and PA-275496-SD)	3	259414
Transformer, current (Kits PA-275499 and PA-275499-SD)	3	255860
Transformer, current (Kits PA-276983 and PA-276983-SD)	3	259793
Transformer, current (Kits PA-276984 and PA-276984-SD)	3	259792

Parts List		
Kits: PA-276187, PA-276188, PA-276189, PA-276190, PA-276986, and PA-276987		
Description	Qty.	Part No.
Lead	2	SWC0-1808-1313
Lead	1	SWC0-1830-1414
Lead	1	SWC1-1830-1414
Lead	1	SWC2-1830-1414
Lead	1	SWC3-1830-1414
Washer, 0.219 x 0.500 x 0.049 in. plain	12	X-25-36
Tie, cable	2	X-468-2
Screw, 10-24 x 0.625 in. r.h.m.	12	X-50-8
Jumper	1	X-6076-2
Nut, 10-24 whiz	12	X-6210-5
Screw, 10-24 x 0.50 in. Phillips® CrimpTite®	4	X-6216-1
Bracket	1	276639
Transformer, current (Kit PA-276187)	3	255860
Transformer, current (Kit PA-276188)	3	253503
Transformer, current (Kit PA-276189)	3	273257
Transformer, current (Kit PA-276190)	3	253610
Transformer, current (Kit PA-276986)	3	259360
Transformer, current (Kit PA-276987)	3	259414

Parts List		
Kit: PA-276988		
Description	Qty.	Part No.
Lead	2	SWC0-1808-1313
Lead	1	SWC0-1830-1414
Lead	1	SWC1-1830-1414
Lead	1	SWC2-1830-1414
Lead	1	SWC3-1830-1414
Washer, 0.219 x 0.500 x 0.049 in. plain	12	X-25-36
Tie, cable	2	X-468-2
Screw, 10-24 x 0.625 in. r.h.m.	12	X-50-8
Jumper	1	X-6076-2
Nut, 10-24 whiz	12	X-6210-5
Transformer, current	3	279272

Parts List		
Kit: PA-275515-SD		
Description	Qty.	Part No.
Lead	2	LW-1608-1414
Lead	1	SWC0-1630-1423
Lead	1	SWC1-1635-1414
Lead	1	SWC2-1635-1414
Lead	1	SWC3-1635-1414
Washer, 0.219 x 0.500 x 0.049 in. plain	12	X-25-36
Tie, cable	2	X-468-2
Screw, 10-24 x 0.625 in. r.h.m.	12	X-50-8
Jumper	1	X-6076-2
Nut, 10-24 whiz	12	X-6210-5
Transformer, current	3	272691